TSE 3003

BURG WÄCHTER

Made in Germany

www.burg-waechter.de



Select Mode

SecuTronic



STSE / SecuTronic – Select Mode

Lite Mode → Professional Mode :

Press the ON/Enter key.
Press the function key.
Press key 2 twice (menu option [Professional Mode]).
Press the ON/Enter key.
Enter your opening code.
Enter your 4-digit code 3195.
Press the ON/Enter key.
To switch to Professional mode, confirm the setting again with the ON/Enter key.

Professional Mode → Lite Mode :

Press the ON/Enter key.
Press the function key.
Select the menu option [Administrator] using keys 1 and 2.
Press the ON/Enter key.
Select the menu option [Lite Mode] using keys 1 and 2.
Enter your valid administrator code.
Enter the 4-digit code 7293.
Press the ON/Enter key.
To switch to Lite-Mode, confirm the setting again with the ON/Enter key.

Important !

All extended settings such as user, calendar, time switch ... are re-set (deleted !) when converting the locking system from Professional Mode to Lite Mode. The first 6 digits of the Administrator code are then the normal user code as only a 6-digit code can be programmed in Lite Mode.

The Professional Mode is not licensed as standard for some safe models. In this case, it can be enabled/activated by purchasing an Opt. Funct. Key (*Optional Function Key*).
See: "TSE _SecuTronic_Operating_instructions_Professional_Mode.pdf"
Sections: - Display Serial numbers
- Input Licence key

Burg-Wächter KG

Altenhofer Weg 15
D - 58300 Wetter
Germany

www.burg-waechter.de
info@burg-waechter.de

BA/A Tr HSE-jwe 12/2005